

Rittal – The System.

Faster – better – everywhere.

Digital Brochure

ENCLOSURES

POWER DISTRIBUTION

CLIMATE CONTROL

IT INFRASTRUCTURE

SOFTWARE & SERVICES

FRIEDHELM LOH GROUP

www.rittal.ca



Comfort Panel



System accessories Page 421 Support arm systems Page 127 Stand systems Page 156

Material:

- Housing: Extruded aluminum section
- Corner pieces: Die-cast zinc
- Corner protectors: Plastic

Color:

- Housing: Natural anodized
- Corner pieces: RAL 7035
- Corner protectors: Similar to RAL 7024

Protection category IP to IEC 60 529:

- IP 65

Protection category NEMA:

- NEMA 12

Supply includes:

- Seals and assembly components for front panels

Note:


- The support arm connection may be swapped over by rotating the enclosure
- 8015.400 and 8015.401 come standard with aluminum front panel included

Approvals:

- UL

Technical details:

Available on the Internet



	Packs of	12 (300)	14 (350)	16 (400)	16 (400)	16 (400)	Page
For front panel height (H) inches (mm)							
For front panel width (B) inches (mm)		16 (400)	18 (450)	20 (520)	20 (520)	20 (520)	
Installation depth inches (mm)		6 (152)	6 (152)	3 (74)	6 (152)	8 (191)	
Model No.	1 pc(s).	8015.400	8015.401	6372.541	6372.542	6372.543	
Weight lb (kg)		22 (10)	25 (11.4)	17 (7.8)	26 (11.7)	30 (13.8)	

Version

Support arm connection □ 120 x 65 mm		–	–	■	–	–	
Support arm connection Ø 130 mm		■	■	–	■	■	
Hinged rear panel with screw lock		–	–	■	–	–	
Hinged rear panel with cam ¹⁾		■	■	–	■	–	
Screw-fastened rear panel ²⁾		–	–	–	–	■	

Accessories

Handle set	1 set(s)	6375.010	6375.010	–	–	–	605
Front panel	1 pc(s).	–	8015.416	6028.014	6028.014	6028.014	608
Mounting bracket for interior fitting	4 pc(s).	6205.100	6205.100	6205.100	6205.100	6205.100	532
Spring nut M5	50 pc(s).	6108.000	6108.000	6108.000	6108.000	6108.000	539
Grounding plate	1 pc(s).	2570.500	2570.500	2570.500	2570.500	2570.500	556

¹⁾ With 3 mm double-bit lock insert, may be exchanged for 41 mm lock inserts, type C, see page 488, plastic handles and T-handles, type C, see page 487.

²⁾ Housing hinged at the front with side double-bit lock insert, may be exchanged for 41 mm lock inserts, type C, see page 488, plastic handles and T-handles, type C, see page 487.

For front panel height (H) inches (mm)	Packs of	20 (500)	20 (500)	20 (500)	24 (600)	24 (600)	24 (600)	Page
For front panel width (B) inches (mm)		20 (520)	20 (520)	20 (520)	20 (520)	20 (520)	20 (520)	
Installation depth inches (mm)		3 (74)	6 (152)	8 (191)	3 (74)	6 (152)	8 (191)	
Model No.	1 pc(s).	6372.551	6372.552	6372.553	6372.561	6372.562	6372.563	
Weight lb (kg)		19 (8.8)	27 (12.3)	34 (15.2)	21 (9.7)	30 (13.5)	37 (16.7)	

Version

Support arm connection □ 120 x 65 mm		■	-	-	■	-	-	
Support arm connection Ø 130 mm		-	■	■	-	■	■	
Hinged rear panel with screw lock		■	-	-	■	-	-	
Hinged rear panel with cam ¹⁾		-	■	-	-	■	-	
Screw-fastened rear panel ²⁾		-	-	■	-	-	■	

Accessories

Handle set		-	-	-	-	-	-	
Front panel	1 pc(s).	6028.015	6028.015	6028.015	6028.016	6028.016	6028.016	608
Mounting bracket for interior fitting	4 pc(s).	6205.100	6205.100	6205.100	6205.100	6205.100	6205.100	532
Spring nut M5	50 pc(s).	6108.000	6108.000	6108.000	6108.000	6108.000	6108.000	539
Grounding plate	1 pc(s).	2570.500	2570.500	2570.500	2570.500	2570.500	2570.500	556

¹⁾ With 3 mm double-bit lock insert, may be exchanged for 41 mm lock inserts, type C, see page 488, plastic handles and T-handles, type C, see page 487

²⁾ Housing hinged at the front with side double-bit lock insert, may be exchanged for 41 mm lock inserts, type C, see page 488, plastic handles and T-handles, type C, see page 487

Configuration Examples

Front panel height inches (mm)	Cut-out dimensions						
16 (400)							
	H = 14" (364 mm) W = 19" (484 mm) 1 = all-round 1" (18 mm) for fastening the adapter plate						
20 (500)							
	H = 18" (464 mm) W = 19" (484 mm) 1 = all-round 1" (18 mm) for fastening the adapter plate						
24 (600)							
	H = 22" (564 mm) W = 19" (484 mm) 1 = all-round 1" (18 mm) for fastening the adapter plate						

Free space, can be used for customer-specific equipment, e.g. switch racks, etc.

HE = U
B = Width (W)